

shot 4 W








instructions for use

For solid ground

1. For **solid grounds** place the ring of the luminaire on the floor and look after a secure stand and that the ring is flush with FFL (finished floor level) – see picture 1.
For **unpaved beds and greens** the shot tee has to be used according to the instructions for use shot tee – see picture 2.
2. Bring the ball on the ring to the desired position. The ball should be tilted only that far, that backwater can't ingress directly into cable- and membrane tunnel – see pictures 3 + 4.
3. Provide the electrical connection between safety plug and grounded electrical socket **aboveground**. Grounded electrical sockets have to correspond to the essential protection class.
4. The safety plug signals the movability of the luminaire.

NOT PERMITTED: Removal of the safety plug – see picture 5.

NOT PERMITTED: Fixed installation and/or a connection with an earth-joint, respectively routing the cable underground. **Underground routing solely with IP44.de connect** and underground connection kit – see pictures 6 + 7.



light technology:

IvyLight-technology
230V Power LED / 3000K
system performance: 4 W/260 lm

**technical information:**

operating voltage 230V / 50Hz
supply cable H05RN-F 3G0,75



protection class



safety class 1



Luminaire is suitable for mounting on normal inflammable fixing surfaces.



conformity mark

maintenance:

Disconnect the electrical installation.

This luminaire contains built-in LED lamps. The lamps cannot be replaced in the luminaire.

dimming:

The luminaire can be dimmed with an approved leading- or trailing edge dimmer. Please contact IP44.de service center for a list of approved dimmers.

care:

Regularly clean luminaire from dirt and deposits. Do not use a high pressure cleaner for cleaning.

Please note care instructions at www.IP44.de.

safety:

We point out that the electric connection of light fixtures has to be done by a certified installer.

We assume no accountability for damages which are a result of non-appropriate mounting or application of the luminaire.

Modifications on the luminaire will result in loss of warranty.

assembly instruction:

The luminaire may not come into contact with highly acidic or alkaline soils, or with other aggressive substances, chemicals, fertilizers or bark mulch.