
shot indoor


instructions for use

1. Place the ring of the luminaire on the floor and look after a secure stand.
2. Bring the ball on the ring to the desired position.
3. Provide the electrical connection between safety plug and grounded electrical socket.



Cord Dimmer:

1. ON/OFF/DIM via push button.
2. Specify setting on the rear side of the device. Switch on light by pushing button. Turn the arrow in an counterclockwise direction to 'MIN' and specify the desired minimal value by pushing the button. Turn the arrow in a clockwise direction to 'MAX' and specify the desired maximum value by pushing the button. Finally, turn the trimmer to the middle position '0'.



light technology:

IvyLight-technology
230V Power LED / 2700K
system performance: 15 W/980 lm
A+ EEC

technical information:

operating voltage 230V / 50Hz
IP20 protection class
safety class 1
Luminaire is suitable for mounting on normal inflammable fixing surfaces.
CE conformity mark

maintenance:

This luminaire contains built-in LED lamps. The lamps cannot be replaced in the luminaire.

safety:

We point out that the luminaire is intended exclusively for indoor use.

We assume no accountability for damages which are a result of non-appropriate mounting or application of the luminaire.

Modifications on the luminaire will result in loss of warranty.